Pressure Sensor

MD-PS002 Pressure sensor core





The MD-PS002 pressure sensor core is a secondary package based on the MD-PS001 pressure sensor chip, which is more convenient for customers to install, and the surface of the sensor is protected by a coating to ensure the performance of the sensor. It is more convenient to be used in air compressors, automotive electronics and other fields that require high cost performance for sensors.

Applications

- Work Industry: air pressure control, cable leak detection, portable pressure gauges, pressure switches and controllers.
- Consumer products: handheld tire pressure gauge, altimeter and barometric pressure gauge.
- Medical Treatment: patient monitoring and diagnostic equipment, sphygmomanometers.
- Section Research: Miniature absolute pressure sensor and general absolute pressure sensor for aerodynamics.


technical paramete


	Minimum	Typical value	Max	unit	Remark
Pressure characteristics					
Pressure range	100KPa 15PSI	200KPa 35 30PSI 50			
greatest pressure		2 times			
Breaking pressure		4 times			
Electrical performance					
Excitation voltage	3	5.0	12	V	
Excitation current		1	3	mA	
input resistance	4	5	6	ΚΩ	
Output impedance	4	5	6	ΚΩ	
Output range					
(FS range) 150KPa	60	80	100	mV	
700KPa	70	100	150	mV	
1700KPa	80	120	180	mV	
Zero output	-25	0	25	mV	
Performance					
Full temperature coefficient	-0.24	-0.19	-0.15	%FS/	Constant voltage power supply
Zero temperature coefficient	-0.07		0.07	%FS/°C	
Temperature Coefficient of Resistance	0.24	0.27	0.33	% /°C	
Linearity	-0.25	0.15	+ 0.25	%FS	
Hysteresis and repeatability		±0.10		%FSO	
Long-term stability		±0.20		%FSO	
Operating temperature	-40		+ 125	°C	
storage temperature	-55		+ 150	°C	







Chip structure











Pin	definition	
1	Input positive power +IN	
2	Output signal +OUT	
3.4	Input negative power-IN	
5	Output signal negative -OUT	

Characteristic curve

Test current: 1.5mA Atmospheric pressure: 101.03Kpa

Humidity: 55%RH





Product Selection Guide

MD-PS002-010A

model	Range
010A	(Absolute pressure 150KPa)
020A	(Absolute pressure 200KPa)
035A	(Absolute pressure 350KPa)
070A	(Absolute pressure 700KPa)
170A	(Absolute pressure 1700KPa)
350A	(Absolute pressure 3500KPa)

>> Pressure Sensor

上海铭动电子科技有限公司 Mingdong Technology (Shanghai) Co.,Ltd. T: (86) 21 5778 0480 F: (86) 21 5156 4102 E: mind@shmind.com www.shmind.com 上海市金山区亭卫公路9299弄73-74号





Absolute pressure bare silicon wafer series

model	Range	
MD-PS001-010A	Absolute pressure 150KPa	
020A	Absolute pressure 200KPa	
035A	Absolute pressure 350KPa	
070A	Absolute pressure 700KPa	
170A	Absolute pressure 1700KPa	
350A	Absolute pressure 3500KPa	

Absolute pressure packaging film series

model	Range		
MD-PS002-010A	Absolute pressure 150KPa		
070A	Absolute pressure 700KPa		

DIP package structure series (gauge pressure)

model	instruction
MD-PSG010-40KPa	The air nozzle is in the same direction as the pi
MD-PSG010R-40KPa	The air nozzle and the pin are reversed
MD-PSG010S-40KPa	SMD pin
MD-PSG010D-100KPa	DIP package structure
MD-PSG070D-700KPa	DIP package structure

Gauge pressure package film series

model	Range	
MD-PS003-0035G	Gauge pressure 35KPa	
010G	Gauge pressure 100KPa	
100G	Gauge pressure 1MPa	
160G	Gauge pressure 1.6MPa	

High temperature diffusion silicon chip series

model	Range
MD-PSG001-010S	SOI high temperature chip 100KPa
020S	SOI high temperature chip 200KPa
100S	SOI high temperature chip 1MPa
200S	SOI high temperature chip 2MPa
400S	SOI high temperature chip 4MPa

Gauge Pressure Bare Silicon Wafer Series

model	Range	
MD-PSG001-004G	Gauge pressure 40KPa	
010G	Gauge pressure 100KPa	
070G	Gauge pressure 700KPa	

NOTE:

- $1.\,Unless \,otherwise \,specified,\,MD-PS001 \,series \,chip \,parameters \,are \,measured \,at \,25^{\circ}C \,and \,1mA \,power \,supply.$
- $2. When used in the range of 0-70 ^{\circ}\text{C}, the performance of the product is better than the above technical parameters.$
- 4. This series of chips can only be used to measure clean gases.
- 5. Each chip has passed electronic probe and visual inspection before leaving the factory to ensure that the factory products are 100% usable.
- 6. All chips are placed in a special plastic protective box for transportation. The package contains the date of manufacture, the number of specific models, and the range. The minimum package is 2000 chips.



